

COMPONENT VALUES FOR VARIOUS HF BANDS		
WA3TFS QRP AMPLIFIER		
160/80/75 METERS		
U\$2	22T #24 ON T50-6 CORE	1.94uH
U\$5, U\$6	21T #24 ON T50-6 CORE	1.8uH
C12, C14	820 pF	
C13	1500 pF	
C9	390pF	
60/40 METERS		
U\$2	18T #24 ON T50-6 CORE	1.3uH
U\$5, U\$6	18T #24 ON T50-6 CORE	1.3uH
C12, C14	430pF	
C13	820pF	
C9	390pF	
30/20/17 METERS		
U\$2	9T #24 ON T50-6 CORE	0.32uH
U\$5, U\$6	11T #24 ON T50-6 CORE	0.5uH
C12, C14	180pF	
C13	330pF	
C9	120pF	